

## **NIGER INFORMATICA**

T.E.: 54 (11) 4941-6300/5035 ~ FAX: 54 (11) 4943-4994 Web: <a href="mailto:http://www.niger.com.ar">http://www.niger.com.ar</a> ~ E-Mail: <a href="mailto:ventas@niger.com.ar">ventas@niger.com.ar</a>

# MotherBoard PCCHIPS M925L

## **Generalidades**

The advanced features of the VIA P4M266 System Board.

- > The Best DDR Solution with AGP4X Graphics Embedded For The Powerful P4 Processors.
- > Supports Intel Pentium 4 1.4~2.0GHz CPUs with frequency at 400MHz FSB in Socket 478 for MicroATX Form Factor



#### **Especificaciones**

- > Provides 2 DIMMs for PC133 SDRAM, 2 DDR DIMM for DDR266 SDRAM modules, and memory size is expand up to 2GB
- > Embedded 3D AGP Graphics Accelerator in North bridge; AGP rev. 2.0 spec. compliant.
- > Provides an AGP slot and 2 PCI slots; supports AGP 4X mode, fully compliant AGP2.0 and PCI 2.2 specification.
- > Provides an CNR slot; DirectSound AC97 Codec on board, for Audio, Modem and Network application.
- > 10/100Mbps Fast Ethernet on board, supports IEEE 802.3 and 802.3u standards, and fully compliant ANSI X3.263 TP-PMD physical sub-layer.
- > Bundled optional an CNR V.90 Fax/Modem card for internet communication.
- > 2MB Flash ROM on board, provides complete Advance Configuration Power Interface (ACPI) and Legacy PMU; Ultra DMA 66/100; fully compliant with PC'97 and PC98 Spec.
- > Provides ATX power connector supports various functions of ATX Power such as Suspend, Shutdown, Wake on LAN, Wake on Modem, Wake on Alarm, Interrupt Wake-Up from Keyboard/Mouse, and Keyboard Power On/Off.
- > Built-in Hardware Monitor circuit supports Thermal, Power and Fan Speed monitor.
- > Supports PC99 Color Connector for easy identification of peripheral devices.
- > Bundled 3Deep, to deliver the precise imagery and display accurate color in your monitor.
- > Bundled Super Voice for Fax/Modem and Voice applications; MediaRing Talk for Internet Phone communication.
- > Bundled Trend Micro's PC-Cillin2000(OEM) for Windows98/Me/NT/2000/XP and internet virus protection.

#### **DRIVERS**

Drivers Page: <a href="http://www.pcchips.com.tw/driver/driver.asp?module\_id=2,3">http://www.pcchips.com.tw/driver/driver.asp?module\_id=2,3</a>